

BS EN 62911:2016



BSI Standards Publication

**Audio, video and information
technology equipment —
Routine electrical safety
testing in production**

bsi.

National foreword

This British Standard is the UK implementation of EN 62911:2016. It is identical to IEC 62911:2016. It supersedes BS EN 50514:2014, which is withdrawn.

The UK participation in its preparation was entrusted to Technical Committee EPL/108, Safety of electronic equipment within the field of audio/video, information technology and communication technology.

A list of organizations represented on this committee can be obtained on request to its secretary.

This publication does not purport to include all the necessary provisions of a contract. Users are responsible for its correct application.

© The British Standards Institution 2016.

Published by BSI Standards Limited 2016

ISBN 978 0 580 87954 8

ICS 33.160.01; 35.020

Compliance with a British Standard cannot confer immunity from legal obligations.

This British Standard was published under the authority of the Standards Policy and Strategy Committee on 31 May 2016.

Amendments/corrigenda issued since publication

Date	Text affected
------	---------------

English Version

**Audio, video and information technology equipment - Routine
electrical safety testing in production
(IEC 62911:2016)**

Appareils audio, vidéo et matériel de traitement de
l'information - Essais individuels de série, en production,
pour la vérification de la sécurité électrique
(IEC 62911:2016)

Audio, Video und Einrichtungen der Informationstechnik -
Stückprüfungen der elektrischen Sicherheit in der Fertigung
(IEC 62911:2016)

This European Standard was approved by CENELEC on 2016-02-10. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard the status of a national standard without any alteration.

Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the CEN-CENELEC Management Centre or to any CENELEC member.

This European Standard exists in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CENELEC member into its own language and notified to the CEN-CENELEC Management Centre has the same status as the official versions.

CENELEC members are the national electrotechnical committees of Austria, Belgium, Bulgaria, Croatia, Cyprus, the Czech Republic, Denmark, Estonia, Finland, Former Yugoslav Republic of Macedonia, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, the Netherlands, Norway, Poland, Portugal, Romania, Slovakia, Slovenia, Spain, Sweden, Switzerland, Turkey and the United Kingdom.



European Committee for Electrotechnical Standardization
Comité Européen de Normalisation Electrotechnique
Europäisches Komitee für Elektrotechnische Normung

CEN-CENELEC Management Centre: Avenue Marnix 17, B-1000 Brussels

European foreword

The text of document 108/616/FDIS, future edition 1 of IEC 62911, prepared by IEC/TC 108 "Safety of electronic equipment within the field of audio/video, information technology and communication technology" was submitted to the IEC-CENELEC parallel vote and approved by CENELEC as EN 62911:2016.

The following dates are fixed:

- latest date by which the document has to be implemented at national level by publication of an identical national standard or by endorsement (dop) 2016-11-10
- latest date by which the national standards conflicting with the document have to be withdrawn (dow) 2018-02-10

This document supersedes EN 50514:2014.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CENELEC [and/or CEN] shall not be held responsible for identifying any or all such patent rights.

Endorsement notice

The text of the International Standard IEC 62911:2016 was approved by CENELEC as a European Standard without any modification.

Annex ZA (normative)

Normative references to international publications with their corresponding European publications

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

NOTE 1 When an International Publication has been modified by common modifications, indicated by (mod), the relevant EN/HD applies.

NOTE 2 Up-to-date information on the latest versions of the European Standards listed in this annex is available here: www.cenelec.eu.

<u>Publication</u>	<u>Year</u>	<u>Title</u>	<u>EN/HD</u>	<u>Year</u>
IEC 60065	-	Audio, video and similar electronic apparatus - Safety requirements	EN 60065	-
IEC 60950-1	-	Information technology equipment - Safety -- Part 1: General requirements	EN 60950-1	-
IEC 62368-1	-	Audio/video, information and communication technology equipment -- Part 1: Safety requirements	EN 62368-1	-

CONTENTS

FOREWORD	3
1 Scope	5
2 Normative references	5
3 Terms and definitions	5
4 Conformance	5
5 Routine electrical safety tests	6
5.1 Resistance of protective bonding system	6
5.2 Electric strength test	6
6 Records of tests	9
Table 1 – Test voltage for equipment with a.c. mains	7
Table 2 – Test voltage for equipment with d.c. mains	7
Table 3 – DC test voltages	8

INTERNATIONAL ELECTROTECHNICAL COMMISSION

**AUDIO, VIDEO AND INFORMATION TECHNOLOGY EQUIPMENT –
ROUTINE ELECTRICAL SAFETY TESTING IN PRODUCTION**

FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 62911 has been prepared by TC108: Safety of electronic equipment within the field of audio/video, information technology and communication technology

The text of this standard is based on the following documents:

FDIS	Report on voting
108/616/FDIS	108/635/RVD

Full information on the voting for the approval of this standard can be found in the report on voting indicated in the above table.

This publication has been drafted in accordance with the ISO/IEC Directives, Part 2.

In this standard, the following print types or formats are used:

- requirements proper and normative annexes: in roman type;

- compliance statements and test specifications: in *italic type*;
- notes/explanatory matter: in smaller roman type;
- normative conditions within tables: in smaller roman type;
- terms that are defined in Clause 3: **bold**.

The committee has decided that the contents of this publication will remain unchanged until the stability date indicated on the IEC website under "<http://webstore.iec.ch>" in the data related to the specific publication. At this date, the publication will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

AUDIO, VIDEO AND INFORMATION TECHNOLOGY EQUIPMENT – ROUTINE ELECTRICAL SAFETY TESTING IN PRODUCTION

1 Scope

This International Standard defines **routine electrical safety test** procedures for use during or after manufacturing of complete equipment, sub-assemblies or components, complying with IEC 60065, IEC 60950-1 or IEC 62368-1 and powered by an **a.c. mains supply** or **d.c. mains supply**, to detect manufacturing failures and unacceptable tolerances in manufacturing and materials.

NOTE All the tests defined in this standard do not necessarily have to be performed at the end product manufacturing location. The optimal location for the **routine electrical safety tests** can be defined by the equipment manufacturer and reviewed under the conformity assessment scheme.

2 Normative references

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60065, *Audio, video and similar electronic apparatus – Safety requirements*

IEC 60950-1, *Information technology equipment – Safety – Part 1: General requirements*

IEC 62368-1, *Audio/video, information and communication technology equipment – Part 1: Safety requirements*

3 Terms and definitions

For the purposes of this document, the terms and definitions given in IEC 60065, IEC 60950-1 and IEC 62368-1, as well as the following apply.

3.1

routine electrical safety test

electrical safety test to which each individual equipment is subjected during or at the end of manufacture

4 Conformance

Equipment shall pass the **routine electrical safety tests** of Clause 5 where applicable and the results of these tests shall be recorded according to Clause 6 prior to shipment from the manufacturing site.

NOTE Practical measures can be used to conduct the test, such as finding an appropriate way to make the connections necessary to perform the relevant test.

5 Routine electrical safety tests

5.1 Resistance of protective bonding system

For **class I equipment**, the continuity of the protective bonding system shall be checked between the protective earth contact of the **mains** plug or appliance inlet, or the **protective earthing terminal** in case of a **permanently connected equipment**, and

- the **accessible** conductive parts that need to be connected to the **protective earthing terminal** for compliance with the requirements of the standard, and
- the protective earth contact of the socket-outlets respectively, if provided to deliver **mains** power to other equipment.

NOTE 1 Functional earth is not considered a part of the protective bonding system and as a consequence, it does not need to be tested.

*The minimum test current is 150 % of the rating of the overcurrent device protecting the **protective bonding conductor** (the **protective current rating**), but not less than 10 A and not more than 25 A (a.c. or d.c.), applied for any duration between 1 s and 4 s. The source shall have a no-load voltage not exceeding 12 V.*

The resistance, calculated from the voltage drop, shall not exceed 0,1 Ω .

*It is permitted to include the power cord (if any) in the resistance measurement and, if the result exceeds 0,1 Ω , to subtract the resistance of the **protective earthing conductor** of the power cord.*

NOTE 2 Ensure that the contact resistance between the tip of the measuring probe and the conductive part under test does not influence the test result.

5.2 Electric strength test

*Routine tests for electric strength shall be carried out between circuits connected to the **mains (primary circuits)** and **accessible** conductive parts. For **accessible** circuits not connected to the **mains (secondary circuits)**, it is permitted to test separately, before final assembly, subassemblies and components, such as transformers, if the relevant insulation cannot be tested in the complete equipment, provided that the complete equipment complies with IEC 60065, IEC 60950-1 or IEC 62368-1 as appropriate.*

The insulation of the equipment shall be checked by the following test:

- *for equipment supplied by an a.c. **mains**, an a.c. test voltage of substantially sine-wave form, having **mains** frequency, or a d.c. test voltage or a combination of both with a peak value as specified in Table 1 is applied;*
- *for equipment supplied by a d.c. **mains**, a d.c. voltage according to Table 2 is applied;*
- *for equipment supplied by either an a.c. **mains** or a d.c. **mains**, the test can be applied at either a.c. or d.c., making sure that the test voltage is the equivalent of the highest of the two required test voltages as given in the above two dashes.*

The test voltages given are the minimum test voltages to be applied. Higher voltages are allowed at the discretion of the manufacturer provided the insulation is not damaged due to overstress by the voltage applied.

NOTE 1 Applying an electrical strength test voltage that is too high can result in deterioration or partial damage of the insulation.

*The test voltage is applied between the supply **terminals** connected together and*

- ***terminals** regarded as **accessible**, and*
- ***accessible** conductive parts respectively,*

that may become **hazardous live (ES3)** in the event of an insulation fault as a result of incorrect assembly.

NOTE 2 **Terminals** regarded as **accessible** and **accessible** conductive parts can be connected together during the electric strength test.

Table 1 – Test voltage for equipment with a.c. mains

Application of test voltage	Test voltage V (peak) a.c. or d.c.	
	Rated mains voltage ≤ 150	Rated mains voltage > 150
Accessible parts connected to protective earth	1 130 (800 r.m.s.)	2 120 (1 500 r.m.s.)
Accessible parts not connected to protective earth	2 120 (1 500 r.m.s.)	3 540 (2 500 r.m.s.)
Functional earth is not considered to be protective earth. Accessible parts connected to functional earth have to be tested as not being connected to protective earth.		

Table 2 – Test voltage for equipment with d.c. mains

Application of test voltage	Test voltage V d.c.	
	Up to and including 60 V	Over 60 V up to and including 10 kV
Accessible parts connected to protective earth	No test	see V_a in Table 3
Accessible parts not connected to protective earth	No test	see V_b in Table 3
Functional earth is not considered to be protective earth. Accessible parts connected to functional earth have to be tested as not being connected to protective earth.		

Table 3 – DC test voltages

DC mains supply voltage	V_a d.c.	V_b d.c.
> 60	921	1 472
62	935	1 495
64	947	1 517
66	962	1 538
68	976	1 560
70	988	1 581
72	1 001	1 602
74	1 014	1 622
76	1 027	1 643
78	1 039	1 663
80	1 052	1 683
85	1 082	1 731
90	1 110	1 777
95	1 138	1 821
100	1 167	1 865
105	1 193	1 909
110	1 219	1 950
115	1 244	1 991
120	1 268	2 031
125	1 294	2 069
130	1 316	2 107
135	1 340	2 145
140	1 363	2 180
145	1 386	2 217
150	1 407	2 253
152	1 414	2 262
^a 155	1 414	2 286
^a 160	1 414	2 320
^a 165	1 414	2 353
^a 170	1 414	2 387
^a 175	1 414	2 419
^a 180	1 414	2 450
^a 184	1 414	2 476
185	1 551	2 482
190	1 571	2 513
200	1 608	2 573
210	1 644	2 631
220	1 681	2 689
230	1 717	2 746
240	1 751	2 800
250	1 783	2 853
260	1 817	2 906
270	1 848	2 958
280	1 881	3 008
290	1 910	3 057
300	1 941	3 105
310	1 971	3 153
320	1 999	3 200
330	2 029	3 247
340	2 057	3 292
350	2 084	3 336

DC mains supply voltage	V_a d.c.	V_b d.c.
360	2 113	3 379
380	2 166	3 466
400	2 219	3 549
420	2 269	3 630
440	2 319	3 709
460	2 367	3 787
480	2 414	3 862
500	2 460	3 937
520	2 506	4 009
540	2 549	4 079
560	2 593	4 149
580	2 636	4 217
588	2 651	4 242
600	2 677	4 242

Linear interpolation is permitted between the nearest two points.

^a At these voltages, the values of V_b are determined by the general curve $V_b = 155,86 U^{0,463}$ ⁸ and are not 1,6 V_a .

Before the test voltage is applied, contact shall be made between the equipment and the connection devices.

The voltage applied to the insulation under test may be gradually raised from zero to the prescribed voltage and maintained at that value for 1 s to 4 s.

*During the test, mains switches and functional switches conductively connected to the **mains**, if any, shall be in the on-position and it shall be ensured by suitable means that the test voltage is effectively connected to the equipment.*

No flash-over or breakdown shall occur during the test. The test voltage source shall be provided with a current sensing (over-current) device which, when activated, gives an indication "unacceptable". When loaded up to and including the overcurrent activation point, the voltage source shall still deliver the prescribed voltage.

NOTE 3 The manufacturer can define the minimum tripping current, making sure it is high enough to detect breakdown but at the same time taking into account possible operator safety issues.

Activation of the current sensing device is regarded as a flash-over or breakdown.

6 Records of tests

All test results should be kept available. The choice of support and format for reports is left to the manufacturer; separate forms (one for each equipment) or lists of equipment, grouped according to the most suitable parameters (periods of time, model, etc.) are equally acceptable.

The only obligation is the availability of data and their immediate interpretability for all equipment leaving the production line.

The following data should be retrievable as evidence that the test was performed:

- date of test,
- model of the equipment,
- serial number of the equipment or another identifier permitting the identification without ambiguity,

- location of the point tested,
- value of earthing circuit resistance with the corresponding current value (*),
- value of voltage applied during the electric strength test (*),
- quick-reference information that the whole set of tests has/has not been successful.

As an alternative to the values marked with an asterisk (*) above, a record of the result of each test (pass or fail) is to be maintained.

British Standards Institution (BSI)

BSI is the national body responsible for preparing British Standards and other standards-related publications, information and services.

BSI is incorporated by Royal Charter. British Standards and other standardization products are published by BSI Standards Limited.

About us

We bring together business, industry, government, consumers, innovators and others to shape their combined experience and expertise into standards-based solutions.

The knowledge embodied in our standards has been carefully assembled in a dependable format and refined through our open consultation process. Organizations of all sizes and across all sectors choose standards to help them achieve their goals.

Information on standards

We can provide you with the knowledge that your organization needs to succeed. Find out more about British Standards by visiting our website at bsigroup.com/standards or contacting our Customer Services team or Knowledge Centre.

Buying standards

You can buy and download PDF versions of BSI publications, including British and adopted European and international standards, through our website at bsigroup.com/shop, where hard copies can also be purchased.

If you need international and foreign standards from other Standards Development Organizations, hard copies can be ordered from our Customer Services team.

Subscriptions

Our range of subscription services are designed to make using standards easier for you. For further information on our subscription products go to bsigroup.com/subscriptions.

With **British Standards Online (BSOL)** you'll have instant access to over 55,000 British and adopted European and international standards from your desktop. It's available 24/7 and is refreshed daily so you'll always be up to date.

You can keep in touch with standards developments and receive substantial discounts on the purchase price of standards, both in single copy and subscription format, by becoming a **BSI Subscribing Member**.

PLUS is an updating service exclusive to BSI Subscribing Members. You will automatically receive the latest hard copy of your standards when they're revised or replaced.

To find out more about becoming a BSI Subscribing Member and the benefits of membership, please visit bsigroup.com/shop.

With a **Multi-User Network Licence (MUNL)** you are able to host standards publications on your intranet. Licences can cover as few or as many users as you wish. With updates supplied as soon as they're available, you can be sure your documentation is current. For further information, email bsmusales@bsigroup.com.

Revisions

Our British Standards and other publications are updated by amendment or revision.

We continually improve the quality of our products and services to benefit your business. If you find an inaccuracy or ambiguity within a British Standard or other BSI publication please inform the Knowledge Centre.

Copyright

All the data, software and documentation set out in all British Standards and other BSI publications are the property of and copyrighted by BSI, or some person or entity that owns copyright in the information used (such as the international standardization bodies) and has formally licensed such information to BSI for commercial publication and use. Except as permitted under the Copyright, Designs and Patents Act 1988 no extract may be reproduced, stored in a retrieval system or transmitted in any form or by any means – electronic, photocopying, recording or otherwise – without prior written permission from BSI. Details and advice can be obtained from the Copyright & Licensing Department.

Useful Contacts:

Customer Services

Tel: +44 845 086 9001

Email (orders): orders@bsigroup.com

Email (enquiries): cservices@bsigroup.com

Subscriptions

Tel: +44 845 086 9001

Email: subscriptions@bsigroup.com

Knowledge Centre

Tel: +44 20 8996 7004

Email: knowledgecentre@bsigroup.com

Copyright & Licensing

Tel: +44 20 8996 7070

Email: copyright@bsigroup.com

BSI Group Headquarters

389 Chiswick High Road London W4 4AL UK

