

**Three phase  
oil-immersed  
distribution  
transformers, 50 Hz,  
from 50 to 2500 kVA  
with highest voltage for  
equipment not  
exceeding 36 kV —**

**Part 4: Determination of the power  
rating of a transformer loaded with  
non-sinusoidal currents —**

**(Implementation of CENELEC  
HD 428.4 S1)**

UDC 621.314.212:621.3.025.3

## Committees responsible for this British Standard

The preparation of this British Standard was entrusted to Technical Committee PEL/14, Power transformers, upon which the following bodies were represented:

Association of Consulting Engineers  
BEAMA Ltd. (Transmission and Distribution Association)  
British Cable Makers Confederation  
British Pump Manufacturers' Association  
British Railways Board  
Electricity Association  
Institution of Plant Engineers  
Transmission and Distribution Association (BEAMA Ltd)

This British Standard, having been prepared under the direction of the Electrotechnical Sector Board, was published under the authority of the Standards Board and comes into effect on 15 October 1995

© BSI 07-1999

The following BSI references relate to the work on this standard:  
Committee reference PEL/14  
Draft announced in *BSI News*, April 1995

ISBN 0 580 24719 8

### Amendments issued since publication

Amd. No.	Date	Comments

---

# Contents

	Page
Committees responsible	Inside front cover
National foreword	ii
<hr/>	
Foreword	2
1 Scope	3
2 Application	3
3 Equivalent power rating	3
4 Calculation of the factor $K$ to obtain the equivalent power rating	3

---

## National foreword

This British Standard has been prepared by Technical Committee PEL/14 and implements HD 484.4 S1:1994, published by the European Committee for Electrotechnical Standardization (CENELEC).

A British Standard does not purport to include all the necessary provisions of a contract. Users of British Standards are responsible for their correct application.

**Compliance with a British Standard does not of itself confer immunity from legal obligations.**

### Summary of pages

This document comprises a front cover, an inside front cover, pages i and ii, the HD title page, pages 2 and 3 and a back cover.

This standard has been updated (see copyright date) and may have had amendments incorporated. This will be indicated in the amendment table on the inside front cover.

---

UDC 621.314.212:621.3.025.3

Descriptors: Electrical transformer, power transformer, three phase transformer, immersed transformer, determination, rating, electrical power

English version

**Three phase oil-immersed distribution transformers, 50 Hz,  
from 50 to 2 500 kVA with highest voltage for equipment  
not exceeding 36 kV**

**Part 4: Determination of the power rating of a transformer  
loaded with non-sinusoidal currents**

Transformateurs triphasés de distribution  
immergés dans l'huile, 50 Hz, de 50 à 2 500 kVA,  
avec une tension la plus élevée pour le matériel ne  
dépassant pas 36 kV  
Partie 4: Détermination de la caractéristique de  
puissance d'un transformateur avec des courants de  
charge non sinusoïdaux

Drehstrom-Öl-Verteilungs-transformatoren 50 Hz  
von 50 bis 2 500 kVA, mit einer höchsten  
Spannung für Betriebsmittel bis 36 kV  
Teil 4: Bestimmung der Bemessungsleistung eines  
Transformators bei nichtsinusförmigen  
Lastströmen

This Harmonization Document was approved by CENELEC on 1993-09-22. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for implementation of this Harmonization Document on a national level.

Up-to-date lists and bibliographical references concerning national implementation may be obtained on application to the Central Secretariat or to any CENELEC member.

This Harmonization Document exists in three official versions (English, French, German).

CENELEC members are the national electrotechnical committees of Austria, Belgium, Denmark, Finland, France, Germany, Greece, Iceland, Ireland, Italy, Luxembourg, Netherlands, Norway, Portugal, Spain, Sweden, Switzerland and United Kingdom.

## **CENELEC**

European Committee for Electrotechnical Standardization  
Comité Européen de Normalisation Electrotechnique  
Europäisches Komitee für Elektrotechnische Normung

**Central Secretariat: rue de Stassart 35, B-1050 Brussels**

## Foreword

This Part 4 of HD 428 was prepared by WG 7, Harmonics, of Technical Committee CENELEC TC 14, Power transformers.

This document was submitted to the Unique Acceptance Procedure (UAP) and was approved by CENELEC as HD 428.4 S1 on 1993-09-22.

The following dates were fixed:

- latest date of announcement of the HD at national level (doa) 1994-03-01
- latest date of publication of a harmonized national standard (dop) 1994-09-01
- latest date of withdrawal of conflicting national standards (dow) 1993-09-01

## 1 Scope

This document gives to the user guidance to determine the loadability of an oil-immersed distribution transformer, as defined in and covered by HD 428, in the case of load current with harmonic factors exceeding the maximum values allowed.

NOTE In general this document is also applicable to dry-type distribution transformers as defined in and covered by HD 538.

## 2 Application

For normal electrical energy distribution, the allowable total harmonic factor<sup>1)</sup> and even harmonic factor of the load current are assumed to be limited to 5 % and 1 % respectively.

For electrical distribution with higher harmonic factors, it has to be taken into account that the load loss increases and, by consequence, the temperature rises in the transformer exceed those corresponding to sinusoidal currents having the same RMS value.

NOTE If the transformer is intended for converter operation, the matter should be discussed between purchaser and manufacturer.

## 3 Equivalent power rating

The equivalent power rating is related to sinusoidal current which causes the same losses as those occurring with the non-sinusoidal current imposed.

The equivalent power rating is equal to the power based on the RMS value of the non-sinusoidal current multiplied by the factor  $K$ .

The rated power of the transformer to be used shall be equal to or higher than the equivalent power rating.

In case a transformer in service is subsequently loaded with harmonic currents, a derating factor  $1/K$  shall be applied to the rated power.

## 4 Calculation of the factor $K$ to obtain the equivalent power rating

The factor  $K$  is given by the following formula<sup>2)</sup>:

$$K = \left[ 1 + \frac{e}{1+e} \left( \frac{I_1}{I} \right)^2 \sum_{n=2}^{n=N} \left( n^q \left( \frac{I_n}{I_1} \right)^2 \right) \right]^{\frac{1}{2}}$$

In the above formula the following symbols and definitions apply:

$e$  = the eddy current loss due to sinusoidal current at fundamental frequency (e.g. 50 Hz), divided by the loss due to a d.c. current equal to the RMS value of the sinusoidal current, both at reference temperature

$n$  = harmonic order

$I$  = the rms value of the sinusoidal current and, in the other case, of non-sinusoidal current, containing all harmonics, given by

$$I = \left( \sum_{n=1}^{n=N} I_n^2 \right)^{\frac{1}{2}} = I_1 \left[ \sum_{n=1}^{n=N} \left( \frac{I_n}{I_1} \right)^2 \right]^{\frac{1}{2}}$$

$I_n$  = the  $n^{\text{th}}$  harmonic current (amplitude or RMS value)

$I_1$  = the fundamental current (amplitude or RMS value)

$q$  = an exponential constant<sup>a</sup>

<sup>a</sup> The exponent  $q$  is dependent on the type of windings and on the frequency. However, as an approximation and as a guidance, the following constant values may be used:

- 1,7 for transformers with round or rectangular wire in both the low and high voltage windings,
- 1,5 for transformers having low voltage foil windings.

Other values, based on measurements and possibly frequency dependent, may be applied by agreement between purchaser and manufacturer.

<sup>1)</sup> The harmonic factor  $H$ , in percentage, is defined by:

$$H\% = 100 \left[ \sum_{n=2}^{n=N} \left( \frac{I_n}{I_1} \right)^2 \right]^{\frac{1}{2}}$$

<sup>2)</sup> In the formula it is assumed that both power ratings are based on the same rms value of the load current.

---

---

## **BSI — British Standards Institution**

BSI is the independent national body responsible for preparing British Standards. It presents the UK view on standards in Europe and at the international level. It is incorporated by Royal Charter.

### **Revisions**

British Standards are updated by amendment or revision. Users of British Standards should make sure that they possess the latest amendments or editions.

It is the constant aim of BSI to improve the quality of our products and services. We would be grateful if anyone finding an inaccuracy or ambiguity while using this British Standard would inform the Secretary of the technical committee responsible, the identity of which can be found on the inside front cover. Tel: 020 8996 9000. Fax: 020 8996 7400.

BSI offers members an individual updating service called PLUS which ensures that subscribers automatically receive the latest editions of standards.

### **Buying standards**

Orders for all BSI, international and foreign standards publications should be addressed to Customer Services. Tel: 020 8996 9001. Fax: 020 8996 7001.

In response to orders for international standards, it is BSI policy to supply the BSI implementation of those that have been published as British Standards, unless otherwise requested.

### **Information on standards**

BSI provides a wide range of information on national, European and international standards through its Library and its Technical Help to Exporters Service. Various BSI electronic information services are also available which give details on all its products and services. Contact the Information Centre. Tel: 020 8996 7111. Fax: 020 8996 7048.

Subscribing members of BSI are kept up to date with standards developments and receive substantial discounts on the purchase price of standards. For details of these and other benefits contact Membership Administration. Tel: 020 8996 7002. Fax: 020 8996 7001.

### **Copyright**

Copyright subsists in all BSI publications. BSI also holds the copyright, in the UK, of the publications of the international standardization bodies. Except as permitted under the Copyright, Designs and Patents Act 1988 no extract may be reproduced, stored in a retrieval system or transmitted in any form or by any means – electronic, photocopying, recording or otherwise – without prior written permission from BSI.

This does not preclude the free use, in the course of implementing the standard, of necessary details such as symbols, and size, type or grade designations. If these details are to be used for any other purpose than implementation then the prior written permission of BSI must be obtained.

If permission is granted, the terms may include royalty payments or a licensing agreement. Details and advice can be obtained from the Copyright Manager. Tel: 020 8996 7070.