

Second edition
2006-04-01

Corrected version
2007-02-01

AMENDMENT 1
2011-03-01

**Rolling bearings — Insert bearings and
eccentric locking collars — Boundary
dimensions and tolerances —**

AMENDMENT 1: Diameter series 3

*Roulements — Roulements «insert» et bagues de blocage
excentriques — Dimensions d'encombrement et tolérances —*

AMENDEMENT 1: Série de diamètres 3



Reference number
ISO 9628:2006/Amd.1:2011(E)

© ISO 2011

PDF disclaimer

This PDF file may contain embedded typefaces. In accordance with Adobe's licensing policy, this file may be printed or viewed but shall not be edited unless the typefaces which are embedded are licensed to and installed on the computer performing the editing. In downloading this file, parties accept therein the responsibility of not infringing Adobe's licensing policy. The ISO Central Secretariat accepts no liability in this area.

Adobe is a trademark of Adobe Systems Incorporated.

Details of the software products used to create this PDF file can be found in the General Info relative to the file; the PDF-creation parameters were optimized for printing. Every care has been taken to ensure that the file is suitable for use by ISO member bodies. In the unlikely event that a problem relating to it is found, please inform the Central Secretariat at the address given below.



COPYRIGHT PROTECTED DOCUMENT

© ISO 2011

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either ISO at the address below or ISO's member body in the country of the requester.

ISO copyright office
Case postale 56 • CH-1211 Geneva 20
Tel. + 41 22 749 01 11
Fax + 41 22 749 09 47
E-mail copyright@iso.org
Web www.iso.org

Published in Switzerland

Foreword

ISO (the International Organization for Standardization) is a worldwide federation of national standards bodies (ISO member bodies). The work of preparing International Standards is normally carried out through ISO technical committees. Each member body interested in a subject for which a technical committee has been established has the right to be represented on that committee. International organizations, governmental and non-governmental, in liaison with ISO, also take part in the work. ISO collaborates closely with the International Electrotechnical Commission (IEC) on all matters of electrotechnical standardization.

International Standards are drafted in accordance with the rules given in the ISO/IEC Directives, Part 2.

The main task of technical committees is to prepare International Standards. Draft International Standards adopted by the technical committees are circulated to the member bodies for voting. Publication as an International Standard requires approval by at least 75 % of the member bodies casting a vote.

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. ISO shall not be held responsible for identifying any or all such patent rights.

Amendment 1 to ISO 9628:2006 was prepared by Technical Committee ISO/TC 4, *Rolling bearings*, Subcommittee SC 6, *Insert bearings and accessories*.

.....

Rolling bearings — Insert bearings and eccentric locking collars — Boundary dimensions and tolerances —

AMENDMENT 1: Diameter series 3

Page 1, Normative references

Delete the date “1998” from ISO 15.

Page 1, Clause 4

In the second paragraph, replace “in Tables 1 to 8” with “in Tables 1 to 12”.

Page 6, 5.3

Replace “to the diameter series 2 of ISO 15:1998” with “to either diameter series 2 or diameter series 3 of ISO 15”.

Page 6, 5.4

In the first sentence of the first paragraph, replace “dimension series 02 of ISO 15:1998” with “dimension series 02 or dimension series 03 of ISO 15”.

Page 6, 5.5

In the second sentence, replace “to dimension series 02 in ISO 15:1998” with “to either dimension series 02 or dimension series 03 of ISO 15”.

Page 6, Clause 6

In the first sentence, replace “given in Tables 1 to 5” with “given in Tables 1 to 5, 9 and 10”.

Page 17, Clause 7

In the first sentence, replace “given in Tables 6 and 7, respectively” with “given in Tables 6, 7 and 11”.

Page 17, Clause 8

In the second paragraph, replace “given in Table 8” with “given in Tables 8 and 12”.

Tables 1 to 8

At the end of the titles of Tables 1 to 8, add “— Diameter series 2”.

After Table 8, insert the following new Tables 9 to 12.

Table 9 — Insert bearings — Wide overall width — Axially extending eccentric locking collar — Diameter series 3 (see Figure 1)

<i>d</i>		<i>D</i>	<i>B</i> ₁ max.	<i>(S)</i>	<i>S</i> ₁ max.	<i>C</i> ^a		<i>C</i> ₁ ^b	<i>C</i> ₂ ^b								
mm	in					min.	max.										
						mm											
25	—	62	46,8	16,7	30,1	17	24	5,6	3								
30	—	72	50,2	17,5	32,7	19	26	6	3								
30,162	1-3/16																
31,75	1-1/4																
33,338	1-5/16																
34,925	1-3/8																
35	—	80	51,6	18,3	33,3	21	28	6,7	3,5								
36,512	1-7/16	90	57,2	19,8	37,4	23	30	7,5	4								
38,1	1-1/2																
40	—																
41,275	1-5/8																
42,862	1-11/16																
44,45	1-3/4	100	58,7	19,8	38,9	25	33	8,3	4								
45	—	110	66,7	24,6	42,1	27	35	9,5	4,5								
47,625	1-7/8																
49,212	1-15/16																
50	—																
50,8	2									120	73	27,8	45,2	29	37	10,3	5
52,388	2-1/16																
55	—																
60	—																
61,912	2-7/16	130	79,4	31	48,4	31	39	11,1	5								
63,5	2-1/2	140	85,7	32,5	53,2	33	41	11,9	5,5								
65	—																
68,262	2-11/16																
70	—																
74,612	2-15/16									150	92,1	34,1	58	35	43	12,7	6
75	—																
76,2	3																
76,2	3	160	100	37,3	62,7	37	46	13,5	6								

Table 9 (continued)

d		D	B_1	(S)	S_1	C^a		C_1^b	C_2^b
mm	in		max.		max.	min.	max.		
			mm		mm	mm			
80	—	170	106,4	40,5	65,9	39	48	14,3	6,5
80,962	3-3/16								
85	—	180	109,5	42	67,5	41	50	15,1	7
87,312	3-7/16	190	115,9	42,1	73,8	43	52	15,9	7
90	—								
95	—	200	122,3	38,9	83,4	45	54	16,7	7,5
100	—	215	129,6	50	79,6	47	58	18,3	8
100,012	3-15/16								
101,6	4								
105	—	225	139,7	48,4	91,3	49	60	19,1	8
110	—	240	141,3	49,2	92,1	50	62	20,6	8,5

^a The minimum and maximum widths are not tolerances; they indicate a range within which the nominal value shall fall.

^b The relubrication means in the outer ring, if used, shall be located on one or both sides of the outer ring zones defined by the dimensions C_1 and C_2 in such a way that lubricant satisfactorily feeds into the bearing from a housing bore groove covering the zone.

Table 10 — Insert bearings — Intermediate overall width — Locking device not axially extending — Diameter series 3 (see Figures 2 and 3)

<i>d</i>		<i>D</i>	<i>B</i> max.	<i>(S)</i>	<i>S</i> ₁ max.	<i>C</i> ^a		<i>C</i> ₁ ^b	<i>C</i> ₂ ^b			
mm	in					mm	mm			mm	min.	max.
											mm	
25	—	62	38	15	23	17	24	5,6	3			
30	—	72	43	17	26	19	26	6	3			
30,162	1-3/16											
31,75	1-1/4											
33,338	1-5/16											
34,925	1-3/8											
35	—	80	48	19	29	21	28	6,7	3,5			
36,512	1-7/16											
38,1	1-1/2											
40	—											
41,275	1-5/8											
42,862	1-11/16	100	57	22	35	25	33	8,3	4			
44,45	1-3/4											
45	—											
47,625	1-7/8											
49,212	1-15/16											
50	—	110	61	22	39	27	35	9,5	4,5			
50,8	2											
52,388	2-1/16											
55	—											
60	—									130	71	26
61,912	2-7/16											
63,5	2-1/2											
65	—											
68,262	2-11/16	150	78	33	45	35	43	12,7	6			
70	—											
74,612	2-15/16											
75	—											
76,2	3									160	82	32
80	—											
80,962	3-3/16											
86	—											
86	—											

Table 10 (continued)

<i>d</i>		<i>D</i>	<i>B</i> max.	<i>(S)</i>	<i>S</i> ₁ max.	<i>C</i> ^a		<i>C</i> ₁ ^b	<i>C</i> ₂ ^b
mm	in					mm	mm		
		mm	mm	mm	mm	mm		mm	mm
85	—	180	96	40	56	41	50	15,1	7
87,312	3-7/16	190	96	40	56	43	52	15,9	7
90	—								
95	—	200	103	41	62	45	54	16,7	7,5
100	—	215	108	42	66	47	58	18,3	8
100,012	3-15/16								
101,6	4								
105	—	225	112	44	68	49	60	19,1	8
110	—	240	117	46	71	50	62	20,6	8,5
120	—	260	126	51	75	55	66	20,6	9
130	—	280	135	54	81	58	72	22,2	9,5
140	—	300	145	59	86	62	76	23,8	10,5

^a The minimum and maximum widths are not tolerances; they indicate a range within which the nominal value shall fall.

^b The relubrication means in the outer ring, if used, shall be located on one or both sides of the outer ring zones defined by the dimensions *C*₁ and *C*₂ in such a way that lubricant satisfactorily feeds into the bearing from a housing bore groove covering the zone.

Table 11 — Tolerances for bearings — Diameter series 3

<i>d</i>		Δ_{dmp}		<i>V</i> _{dsp}
>	≤	high	low	max.
mm		μm		μm
24	30,162	+18	0	12
30,162	50	+21	0	14
50	80,962	+24	0	16
80,962	120	+28	0	19
120	140	+33	0	22

NOTE Tolerance values are applicable to finished bores, whether or not the bore is plated or treated.

Table 12 — Radial internal clearances — Diameter series 3

<i>d</i>		<i>D</i> mm	Group N		Group 3	
mm	in		min.	max.	min.	max.
			µm		µm	
25	—	62	12	28	23	41
30 30,162	— 1-3/16	72				
31,75 33,338 34,925 35 36,512	1-1/4 1-5/16 1-3/8 — 1-7/16	80	13	33	28	46
38,1 40	1-1/2 —	90				
41,275 42,862 44,45 45	1-5/8 1-11/16 1-3/4 —	100	14	36	30	51
47,625 49,212 50	1-7/8 1-15/16 —	110				
50,8 52,388 55	2 2-1/16 —	120	18	43	38	61
60 61,912	— 2-7/16	130				
63,5 65	2-1/2 —	140				
68,262 70	2-11/16 —	150	20	51	46	71
74,612 75 76,2	2-15/16 — 3	160				

Table 12 (continued)

<i>d</i>		<i>D</i> mm	Group N		Group 3	
mm	in		min.	max.	min.	max.
			µm		µm	
85	—	180	24	58	53	84
87,312	3-7/16	190				
90	—	200				
95	—	200				
100	—	215	28	66	61	97
100,012	3-15/16					
101,6	4					
105	—	225	33	81	71	114
110	—	240				
120	—	260				
130	—	280	33	81	71	114
140	—	300				

ICS 21.100.20

Price based on 7 pages